

## RG59 Cable B/U Dual Fig 8

<b>BATT Part No:</b>	49123
<b>Application:</b>	Coaxial cables are used in high frequency transmission, especially for transmitters and receivers, computers, radio and TV transmissions.
<b>Conductor:</b>	2 x 0.27sqmm (1/0.58) Copper Clad Steel
<b>Insulation:</b>	3.71 +/-0.10mm Solid PE
<b>Armour:</b>	PCWB
<b>Braid:</b>	16/7/0.12mm Bare copper wire (coverage: min 95%)
<b>Sheath:</b>	6.20+/-0.15mm PVC
<b>Colour:</b>	Black
<b>Impedance:</b>	75 Ohm
<b>Capacitance:</b>	67 pF/M
<b>Attenuation at 20°C:</b>	5 MHz: 2.60 dB/100m 10 MHz: 3.00 dB/100m 50MHz: 8.5 dB/100m 100MHz: 10.9 dB/100m 200 MHz: 16.10 dB/100m 300 MHz: 19.70 dB/100m 470MHz: 25 dB/100m 600 MHz: 29.50 dB/100m 1000MHz: 39.1 dB/100m

