


## TelCleat

Black low-density polyethylene - unaffected by corrosive environments, oils & many chemicals  
 suitable for cables 10-51mm in diameter  
 8 sizes in range  
 overlapping self adjusting ranges  
 sunlight (UV) and weather resistant  
 one piece single fixing design  
 can be double stacked on one fixing  
 operating temperature -70 to +70°C

| CABLE DIA |      | HEIGHT (B) |     | WIDTH (C) | DEPTH | WEIGHT g | BATT PART NUMBER | SIZE |
|-----------|------|------------|-----|-----------|-------|----------|------------------|------|
| MIN       | MAX  | MIN        | MAX |           |       |          |                  |      |
| 10.5      | 14.5 | 15         | 18  | 32        | 12    | 2.3      | 90010            | 01   |
| 12.2      | 16.7 | 17         | 22  | 36        | 14    | 3.4      | 90011            | 02   |
| 14.6      | 19.8 | 21         | 26  | 43        | 16    | 5.5      | 90012            | 03   |
| 17.7      | 24.0 | 25         | 31  | 51        | 18    | 8.6      | 90013            | 04   |
| 21.7      | 28.5 | 30         | 37  | 57        | 20    | 12.4     | 90014            | 05   |
| 26.2      | 34.2 | 35         | 43  | 65        | 22    | 16.4     | 90015            | 06   |
| 31.9      | 41.6 | 42         | 52  | 78        | 25    | 24       | 90016            | 07   |
| 39.3      | 51.1 | 50         | 62  | 91        | 26    | 35       | 90017            | 08   |



### Method of fixing

The cleat is opened up and placed around the cable so that the end of the cleat containing the slot will be in contact with the mounting surface, except for the 90010, which should be reversed to put the slot uppermost. In this case an M5 washer should be used to prevent the nut entering the slot of the cleat

When mounting directly on unistrut or leprack type channel section an adapter plate should be used

[battindustrial.sales@batt.co.uk](mailto:battindustrial.sales@batt.co.uk)